# **NoVus**

## Digital Video Recorder

## **NDR-BA5104**





#### **KEY FEATURES**



















- •Video channels: 4, audio channels: 2
- •IP video channels: 1
- ullet Recording speed up to 100 fps (analog) + up to 12 fps
- •Internal HDDs mount: up to 1
- •Monitor outputs (main): 3
- · Advanced network software
- •Supports 700 TVL cameras (960H)
- •IP cameras support (hybrid mode)

#### **COMPLIANCE**







#### **DIMENSIONS**



#### **VIDEO**

Video Input	4 x BNC
IP Cameras	Channels number: 1 at 1920 x 1080 resolution *
Monitor Output	main (split screen, full screen, sequence): 1 x HDMI, 1 x VGA, 1 x BNC

#### **AUDIO**

Audio Input/Output	2 x RCA/1 x RCA
Audio Input/Output	2 x RCA/1 x RC

#### RECORDING

KECOKDING	
Compression	H.264
Recording Speed	100 fps (960 x 576) • 100 fps (720 x 576) • 100 fps (720 x 288) • 100 fps (360 x 288)
Recording Speed (IP Cameras)	6 fps (1 x 6 fps for 1920 x 1080) • 12 fps (1 x 12 fps for 1280 x 720)
IP Stream Size	6 Mb/s in total from all cameras
Recording Mode	time-lapse, triggered by: REC/PANIC button, motion detection
Schedule	individual settings for: each camera, each day of the week,

configuration with an accuracy of: 60 min, possibility of combining

#### Prealarm/Postalarm up to 30 s/up to 5 min

#### **PLAYBACK**

Playback Speed (analog channels)	100 fps (25 fps per channel)
Playback Speed (IP channels)	12 fps (12 fps per channel)
Recorded Data Search	by date/time, events

individual recording modes

#### **BACKUP**

Backup Methods	USB port (HDD or Flash memory), network	
Backup File Format	AVI, DAT	
STORAGE		

Internal storage	available mount: 1 x HDD 3.5" SATA (without DVD-RW) **
Total Capacity	4 TB

#### **ALARM**

Motion Detection	22 x 15 grid, individual settings of sensitivity
System Reaction to Alarm Events	buzzer, e-mail, screen message, recording activation

#### **NETWORK**

Network Interface	1 x Ethernet - RJ-45 interface, 10/100 Mbit/s
PC/MAC Software	B-Viewer, CMS, NMS, Internet Explorer/-
Mobile applications	SuperLivePro (iPhone, Android), SuperLiveHD (iPhone, Android)







# Digital Video Recorder NDR-BA5104

Max. Number of Connections with DVR

7 (live monitoring: 5, playback: 1, configuration: 1)

#### PTZ

PTZ Ports	1 x RS-485
PTZ Protocols	N-Control, Pelco-D, Pelco-P, others
PTZ Functions	pan/tilt/zoom, preset commands, patterns, tours, auto-scans

#### **AUXILIARY INTERFACES**

USB Ports 2 x USB 2.0

### **OPERATING SYSTEM**

Operating System	Linux
Operation Mode	quadruplex
OSD	languages: Polish, English, Russian, others
Control	front panel, IR remote controller, PC mouse (in-set included), network, NV-KBD70, NV-KBD50, NV-KBD30 keyboards
System Diagnostic	automatic control of: HDDs

INSTALLATION PARAMETERS	
Dimensions (mm)	300 (W) x 65 (H) x 280 (D)
Weight	2 kg (without HDDs)
Power Supply	12 VDC (100 ~ 240 VAC/12 VDC PSU in-set included)
Power Consumption	25 W (with 1 HDD)
Operating Temperature	0°C ~ 50°C

 $<sup>\</sup>ast$  Feature available for DVRs with 3.4.3.U-3520D-11 2015-02-01 (Launch date) or later firmware version. DVR is compatible with Novus IP 3000 cameras.





<sup>\*\*</sup> List of compatible HDD models and maximum of their capacities is available in section DOWNLOADABLE FILES.