NoVus

8-channel IP Recorder

NVR-4408P8-H1/F-II





KEY FEATURES



























- •8 x video and audio channels
- $\bullet Recording$ speed up to 240 fps at 3840 x 2160
- $\bullet \, \text{Recorded}$ stream size: 128 Mb/s in total from all
- •1 x internal place for HDD mounting
- •2 x monitor outputs (HDMI 4K UltraHD, VGA)
- Face recognition

COMPLIANCE



DIMENSIONS



The recorder is dedicated to work with NOVUS 4000 series IP cameras. Detailed data can be found in the compatibility table available in the $\ensuremath{\mathsf{DOWNLOADABLE}}$ FILES tab.

VIDEO	
IP Cameras	up to 8 channels at 3840 x 2160 resolution (video + audio)
Maximum Supported Camera Resolution	3840 x 2160 • 4000 x 3000 for fisheye cameras
Compression	H.264, H.264+, H.265, H.265+
Monitor Output	main (split screen, full screen, sequence): 1 x HDMI (4K UltraHD), 1 x VGA (up to 2 monitors simultaneously)
Dualstreaming Support	yes
Fisheye Support	using Internet Explorer, RXCamView, NHDR-5000Viewer, N Control 4000
AUDIO	
Audio Input/Output	- / 1 x HDMI, 1 x line-out (RCA)
RECORDING	
Recording Speed	240 fps (8 x 30 fps for 3840 x 2160 and lower)
Stream Size	128 Mb/s in total from all cameras
Recording Mode	continuous, triggered by: manual, alarm input, motion detection, face recognition, intelligent image analysis functions, PIR alarm, downloading camera records after restoring network connection (ANR)
Prealarm/Postalarm	up to 3 s/up to 600 s
DISPLAY	
Display Speed	240 fps (8 x 30 fps)
PLAYBACK	
Playback Speed	240 fps (8 x 30 fps)
Recorded Data Search	by date/time, events, image analysis events, motion in a defined area, related to face recognition, tags
BACKUP	
Backup Methods	USB port (HDD or Flash memory), network
Backup File Format	JPG, BMP, PNG, MP4, AVI, RF
STORAGE	
Internal Storage	available mount: 1 x HDD 3.5" 8 TB SATA

network HDD (NFS or SMB/CIFS)



Total Internal Capacity External storage

NoVus

8-channel IP Recorder NVR-4408P8-H1/F-II

Total External Capacity	8 TB	
ALARM		
Camera Alarm Input/Output	supports IP camera's alarm input/output	
System Reaction to Alarm Events	buzzer, e-mail, alarm output activation, screen message, recording activation, PTZ, Full Screen, FTP picture upload, FTP video upload, picture to Cloud, video to Cloud, voice prompt	
INTELLIGENT IMAGE ANALYSI	s	
Supported Functions	Exception, Tripwire, Zone entrance, Abandoned Object, Object Disappearance, Crowd detection, Face Detection, Face Recognition (in cooperation with selected 4000 series cameras), Pedestrian Detection, Cross Counting, Sound detection, Perimeter Intrusion Detection by pedestrian or vehicle, Line Cross Detection by pedestrian or vehicle, License Plate Recognition (LPR), Objects Distinguishing, Queue Lenght Detection, Heat Map, Cross Counting by pedestrian or vehicle	
NETWORK		
Network Interface	1 x Ethernet - RJ-45 interface, 10/100/1000 Mbit/s • 8 x Ethernet PoE (IEEE802.3af, Class 3) - RJ-45 interface, 10/100 Mbit/s	
Network Protocols Support	HTTP, TCP/IP, IPv4/v6, HTTPS, FTP, DHCP, DNS, DDNS, NTP, RTSP, UPnP, SNMP, PPPoE, SMTP, P2P, HTML5	
PC/MAC Software	NOVUS MANAGEMENT SYSTEM VSS, NOVUS MANAGEMENT SYSTEM AC, NMS, Internet Explorer, NHDR-5000 Viewer, Firefox, Chrome, Opera, Edge, N Control 4000/Safari, NHDR-5000 Viewer, N Control 4000	
Mobile applications	RxCamView (iPhone, Android)	
Number of Simultaneous Connectio	nsup to 32 users, each user up to 5 devices	
Bandwidth	128 Mb/s in total to all client workstations	
PTZ		
PTZ Functions	pan/tilt/zoom, preset commands, patterns	
AUXILIARY INTERFACES		
USB Ports	2 x USB 2.0	
ODERATING CYCTEM		
OPERATING SYSTEM Operating System	Linux	
OSD	languages: Polish, English, others	
Control	PC mouse and IR remote controller (in-set included), network	
System Diagnostic	automatic control of: HDDs, network, camera connection loss	
Security	password protection, IP filtering	
•	passassas,	
INSTALLATION PARAMETERS		
Dimensions (mm)	300 (W) x 53 (H) x 227 (D)	
Weight	1.1 kg (without HDD)	
Power Supply	48 VDC (100 ~ 240 VAC/48 VDC PSU in-set included)	
Power Consumption	20 W (with 1 HDD) + 59 W PoE	
Operating Temperature	-10°C ~ 45°C	







8-channel IP Recorder NVR-4408P8-H1/F-II

The availability of individual functions (including image analysis) depends on the model of the cameras used, as well as the software version of the recorder and cameras.

In order to create face recognition system, please deploy NOVUS 4000 series IP cameras with "F" in the model name.

Presented display and playback speeds are achieved using dual-streaming. Detailed data on hard drives can be found in the compatibility table available in the DOWNLOADABLE FILES tab.



